

MaizeDMX Playback Controller

User Manual



Features

- MIDI Controller designed for stage lighting applications.
- 45 mechanical keys with blue backlight, 11 LED indicators and 11 faders.
- Big Go and Back buttons for easy cue to cue execution.
- 10 X-keys for quick custom actions.
- Seamless integration with MaizeDMX (version 3.4.0 or later).
- Use with any other software with MIDI controller support.

MIDI Messages

This controller will show up as an MIDI input and output device with the name “USB2.0-MIDI”. The MIDI note and controller number are as the following, all messages are sent on MIDI channel 0. You can turn on and off backlight and LED by sending MIDI note on/off message to the output device.

Channel Strips:

Button 1	0	1	2	3	4	5	6	7	8	9	10
Button 2	15	16	17	18	19	20	21	22	23	24	25
Button 3	30	31	32	33	34	35	36	37	38	39	40
LED	45	46	47	48	49	50	51	52	53	54	55
Fader CC#	0	1	2	3	4	5	6	7	8	9	10

X Buttons:

X1	X2	X3	X4	X5	X6	X7	X8	X9	X10
11	12	26	27	41	42	43	28	44	29

GO button note: 13

Back button note: 14

Specification

Buttons	45 mechanical keys with blue backlight
LED	11
Fader	11 x 60mm faders
Connection	USB 2.0 type B to A cable included
Product Weight	4lb 13oz, 2.184kg
Product Size	34.4 x 24 x 2.4mm (without rubber feet)
Shipping Weight	5lb 7oz, 2.5kg
Shipping Size	41 x 29 x 6.5 mm, 16 x 12 x 3 inch